














Schéma	Vhodné podomietkové batérie
	 Priama montáž do steny RS 062, NO 062, TD 062, TD F 062, CL 062, CR 064  Použitie R-boxu RB 070.50 RS 066, NO 066, CR 066, TD 066, TD F 066, CL 066  Použitie R-boxu Vari RB 072.50 FL 066
	 Priama montáž do steny RS 061, NO 061, TD 061, TD F 061, CL 061  Použitie R-boxu RB 070.50 RS 065, NO 065, CR 065, TD 065, TD F 065, CL 065  Použitie R-boxu Vari RB 072.50 FL 065
	 Priama montáž do steny CR 063
	 Použitie R-boxu RB 071.50 CR 067.00

HODNOTY PRIETOKU VODOVODNÝCH BATÉRIÍ RAVAK								
Prietok je udávaný v l/min pri tlaku 0,3MPa								
RAVAK kód	Umývadlo	Bidet	Vaňa	Hlavová sprcha	Ručná sprcha	OUT 1	OUT 2	OUT 3
PU 014.00	12							
PU 014.20	12							
PU 015.00	12							
PU 015.20	12							
PU 016.00	12							
PU 016.20	12							
PU 019.00	15							
PU 019.20	15							
PU 022.00/150			19		11			
PU 022.20/150			19		11			
PU 026.00			21		9			
PU 026.20			21		9			
PU 032.00					23			
PU 032.20					23			
PU 033.00/150					22			
PU 033.20/150					22			
PU 055.00		12						
PU 055.20		12						
FL 013.00	12							
FL 013.20	12							
FL 014.00	12							
FL 014.20	12							
FL 016.00	13							
FL 016.20	13							
FL 022.00			21		24			
FL 022.20			21		24			
FL 026.00			17		11			
FL 026.20			18		11			
FL 032.00					22			
FL 032.20					22			
FL 055.00		12						
FL 055.20		12						
FL 065.00						25	25	
FL 065.20						25	25	
FL 066.00						25		
FL 066.20						26		
TE 023.00/150			21		22			
TE 033.00/150					24			
TE 072.00/150					23			
TE 082.00/150			21		26			
TE 091.00/150				19	12			
TE 092.00/150			17	12	10			
TE 093.00/150				14	11			
TE 092.01			17	12	10			
TE 093.01				14	11			
TD F 011.00	5							
TD F 011.20	5							
TD F 012.00	5							
TD F 012.20	5							
TD F 013.00	5							
TD F 013.20	5							
TD F 014.00	5							
TD F 014.20	5							
TD F 015.00	5							
TD F 015.20	5							
TD F 022.00/150			19		21			
TD F 022.20			19		21			
TD F 032.00/150					21			
TD F 032.20					21			
TD F 033.00/150					22			
TD F 033.20					21			
TD F 055.00		14						
TD F 055.20		14						
TD F 061.00						22	21	
TD F 061.20						22	21	
TD F 062.00						26		
TD F 062.20						26		
TD F 065.00						21	21	
TD F 065.20						21	21	
TD F 066.00						22		
TD F 066.20						22		
TD F 091.00/150				14	11			
TD F 091.20				14	11			

Schéma	Vhodné podomietkové batérie
	 Priama montáž do steny RS 062, NO 062, TD 062, TD F 062, CL 062, CR 064  Použitie R-boxu RB 070.50 RS 066, NO 066, CR 066, TD 066, TD F 066, CL 066  Použitie R-boxu Vari RB 072.50 FL 066
	 Priama montáž do steny RS 061, NO 061, TD 061, TD F 061, CL 061  Použitie R-boxu RB 070.50 RS 065, NO 065, CR 065, TD 065, TD F 065, CL 065  Použitie R-boxu Vari RB 072.50 FL 065
	 Priama montáž do steny CR 063
	 Použitie R-boxu RB 071.50 CR 067.00

HODNOTY PRIETOKU VODOVODNÝCH BATÉRIÍ RAVAK									
Prietok je udávaný v l/min pri tlaku 0,3MPa									
RAVAK kód	Umývadlo	Bidet	Vaňa	Hlavová sprcha	Ručná sprcha	OUT 1	OUT 2	OUT 3	
TD 011.00	5								
TD 012.00	5								
TD 013.00	5								
TD 014.00	5								
TD 015.00	5								
TD 022.00/150			19		21				
TD 032.00/150					21				
TD 033.00/150					22				
TD 055.00		14							
TD 061.00						22	21		
TD 062.00						26			
TD 065.00						21	21		
TD 066.00						22			
TD 091.00/150				14	11				
CR 011.00	8								
CR 012.00	8								
CR 015.00	8								
CR 016.00	14								
CR 019.00	8								
CR 022.00/150			16		17				
CR 025.00			16		11				
CR 032.00/150					20				
CR 055.00		15							
CR 063.00						20	20		
CR 064.00						20			
CR 065.00						21	20		
CR 066.00						21			
CR 067.00						16	17	17	
CR 080.00			19		14				
CR 112.00	7				6				
CR 112.01	7				6				
CL 011.00	11								
CL 012.00	11								
CL 016.00	7								
CL 022.00/150			15		16				
CL 032.00/150					17				
CL 055.00		10							
CL 061.00						22	23		
CL 062.00						24			
CL 065.00						20	20		
CL 066.00						20			
SN 011.00	16								
SN 012.00	16								
SN 015.00	16								
SN 016.00	16								
SN 022.00/100			15		17				
SN 022.00/150			17		17				
SN 032.00/100					20				
SN 032.00/150					21				
SN 041.00/100	17								
SN 041.00/150	17								
WF 025.00			19		11				
RS 025.00			19		12				
FM 016.00	18								
FM 080.00			16		12				
FM 081.00			19		15				
BM 011.00	11				6				
BM 011.01	11				6				
BM 040.00					9				
BM 040.01					9				
DS 091.00				15	8				
DS 092.00				15	8				